



SPA 3220
240W - 260W Mixing Amplifier

Siera manufactures reliable and affordable solutions in Electronic Security, CCTV, Access Control, Intercommunications, Professional Audio and Automation.

Featured specifications

- 5 input channels
- Microphone priority function
- Pre Output connector
- Low impedance output
- Self protection circuit
- Rated power: 240W - 260W

Output power:	240W - 260W
AC Power consumption:	350W
Distorsion:	<0,5 % (1/3 rated power at 1 KHz)
S/N ratio:	Line: 85 dB, MIC: >72 dB
Inputs:	MIC 1: 600 Ohms, 5-8 mV MIC 2: 600 Ohms, 5-8 mV MIC 3: 600 Ohms, 5-8 mV AUX 1: 10K Ohms, 150-470 mV AUX 2: 10K Ohms, 150-470 mV
Activated Priority:	On MIC 1
Frecuency response:	60 Hz to 15 KHz +/- 3dB
Tone controls:	Bass boost: +/- 10dB at 100 Hz Trebble boost: +/- 10dB at 12
Speaker outputs:	KHz 4-16 Ohms, 70V/100V
Power supply:	Optional
Net weight:	14.8 Kg Approx
Dimensions:	89 (H) x 483 (W) x 320 (D) mm

